

Numéro de certificate / Certificate No.: **LS250054GCC-0**

Date de délivrance / Date of issue: 2025-05-27

Valide jusqu'au / Valid until: Indéfiniment / Indefinitely

Demandeur / Applicant:	Shenzhen SOFARSOLAR Co., Ltd. 11/F., Gaoxinqi Technology Building, No.67 Area, Xingdong Community, Xin'an Sub-district, Bao'an District, Shenzhen City, P.R.China		
Produit / Product:	Onduleurs photovoltaïques / PV inverter		
Modèle(s) / Model(s):	SOFAR 3KTLM-G3, SOFAR 4.6KTLM-G3,, SOFAR 6KTLM-G3	SOFAR 3.6KTLM-G3, SOFAR 5KTLM-G3,	SOFAR 4KTLM-G3, SOFAR 5KTLM-G3-A,
Données techniques / Technical data:	Puissance assignée / Rated output power [W]: 3000 ~ 6000 Tension nominale AC / Nominal output AC voltage [V]: 230 (L + N + PE, 50 Hz) (Pour plus de détails, voir A.2 à la p.2 / For further details see A.2 on p.2.)		
Marque / Trademark:			
Version du logiciel / Software Version:	V000001		
Règlements et normes appliqués / Regulations and standards applied:	EN 50549-1:2019 + A1:2023 Requirements for generating plants to be connected in parallel with distribution networks - Part 1-1: Connection to a LV distribution network - Generating plants up to and including Type B EN 50549-10, October 2022 Requirements for generating plants to be connected in parallel with distribution networks - Part 10: Tests for conformity assessment of generating units		
Schéma de certification / Certification scheme:	CMPD-01		
Numéro du rapport de test / Test report no.:	HC2411290275GC04 (2025-05-22)		

Les unités de production mentionnées ci-dessus sont certifiées pour les modules de production de **type A**.

Ce certificat confirme que les unités de production mentionnées, avec le logiciel correspondant, répondent aux exigences des normes / directives de référence au moment de l'émission du certificat.

Les unités de production sont considérées conformes aux articles pertinents (voir Annexe H, EN 50549-1:2019) du Règlement (UE) 2016/631 de la Commission du 14 avril 2016 établissant un code de réseau relatif aux exigences de raccordement au réseau pour les générateurs (NC RfG), à condition que tous les paramètres définis par le gestionnaire de réseau de distribution (GRD) et la partie responsable soient respectés. /

The above-mentioned generating unit(s) are certified for **type A** generating modules.

This certificate confirms that the above-mentioned generating unit(s) with corresponding software meet the requirements of the referenced standard(s) / guideline(s) at the time of issuance of the certificate.

The generating units are considered to be compliant with the relevant articles (see Annex H, EN 50549-1:2019) of Commission Regulation (EU) 2016/631 of 14 April 2016 establishing a network code on requirements for grid connection of generators (NC RfG), provided that all settings as specified by the DSO and responsible party are complied with.

This certificate relates to type testing and does not imply LYNS's endorsement, approval, certification or on-going control of the product(s), either in terms of performance, design, manufacture or materials used. This certificate and the results stated herein relate solely to the sample product(s) tested and to the specific tests undertaken.

The certificate will remain valid for the stated period providing no changes are made to the product, production method etc. This certificate is only valid when this is also found at <http://www.lyns-tci.com/en/certificate-search> or contact Lyns-tci Technology Guangdong Co., Ltd..

This certificate is for the exclusive use of LYNS's Client and is provided pursuant to the agreement between LYNS and its Client. LYNS's responsibility and liability are limited to the terms and conditions of the agreement. LYNS assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned using this verification.

The certificate is comprised of 8 pages (including Annex of 7 pages).

Dongguan, 2025-05-27

Dipl.-Ing. Weizhao Zheng
Head of certification body

Certification body Lyns-tci Technology Guangdong Co., Ltd. accredited according to ISO/IEC 17065 for product certification.

This document shall not be reproduced, except in full, without the written approval of Lyns-tci Technology Guangdong Co., Ltd.

A.1 Historique de la révision du certificat / Revision history of the certificate

Rév. n°. / Rev. No.	Date / Date	Modifications / Changes
0	2025-05-27	Première édition / Initial issue

A.2 Données techniques de la (des) unité(s) de génération / Technical data of the generating unit(s)

Modèle / Model	SOFAR 3KTLM-G3	SOFAR 3.6KTLM-G3	SOFAR 4KTLM-G3	SOFAR 4.6KTLM-G3,
Entrée photovoltaïque (DC)				
Tension d'entrée max / Max. DC input voltage [V]	600			
Plage de tension MPP / Operating MPPT voltage range [V]	80 ~ 550			
Courant d'entrée max. utile / Max. input DC current [A]	15 / 15			
Connexion AC / AC connection				
Phases de connexion / Connection phases	☒ Monophasé / Single-phase ☐ Triphasé / Three-phase			
Tension nominale AC / Nominal output AC voltage [V]	230 (L + N + PE, 50 Hz)			
Courant de sortie max. / Max. output AC current [A]	15.0	16.0	20.0	23.0
Puissance assignée / Nominal active output power [W]	3000	3680	4000	4600
Puissance apparente max. / Max. apparent output power [VA]	3300	3680	4400	4600

Model	SOFAR 5KTLM-G3	SOFAR 5KTLM-G3-A	SOFAR 6KTLM-G3
Entrée photovoltaïque (DC)			
Tension d'entrée max / <i>Max. DC input voltage</i> [V]	600		
Plage de tension MPP / <i>Operating MPPT voltage range</i> [V]	80 ~ 550		
Courant d'entrée max. utile / <i>Max. input DC current</i> [A]	15 / 15		
Connexion AC / <i>AC connection</i>			
Phases de connexion / <i>Connection phases</i>	☒ Monophasé / <i>Single-phase</i> ☐ Triphasé / <i>Three-phase</i>		
Tension nominale AC / <i>Nominal output AC voltage</i> [V]	230 (L + N + PE, 50 Hz)		
Courant de sortie max. / <i>Max. output AC current</i> [A]	25.0	21.7	29.0
Puissance assignée / <i>Nominal active output power</i> [W]	5000	5000	6000
Puissance apparente max. / <i>Max. apparent output power</i> [VA]	5500	5000	6000

Plage de température de fonctionnement / Operating temperature range	-30°C ~ +60°C
Indice de protection / Degree of protection	IP65
Classe de protection / Protection class	I
Catégorie de surtension / Overvoltage category	AC: III; DC: II
Topologie / Topology	Sans transformateur / No galvanic isolation
Version du logiciel / Software Version	V000001

Fabricant / Manufacturer	Guangdong Sofar Smart Solar Technology Co., Ltd. No.1, Dongsheng North Road, Chenjiang Street, Zhongkai High-tech Zone, Huizhou City, Guangdong Province, P.R.China (Jedna licencja, wiele adresów / One license multiple addresses)
--------------------------	--

A.3 Remarques pour l'essai de type / Remarks for type testing

Laboratoire d'essais / Testing laboratory	Lyns-tci Technology Guangdong Co., Ltd. Room 1201, Unit 2, Building 18, No. 7, Science and Technology Boulevard, Houjie Town, Dongguan City, Guangdong, 523960 P.R.C (Accrédité selon / Accredited acc. ISO/IEC 17025: A2LA Accréditation n°. / Accreditation no. 5200.02)
Lieu d'essai / Testing location	Idem que ci-dessus / Same as above
Période de mesure / Measurement period	2024-12-05 ~ 2025-05-09

A.4 Évaluation de la conformité / Conformity assessment

Sur la base des résultats d'essai soumis, le présent certificat atteste de la conformité suivante selon les normes EN 50549-1 / Based on the test results submitted, this certificate provides the following conformity assessment according to EN 50549-1:

Clause(s) / subclause(s) of EN 50549-1:2019 or EN 50549-2:2019	Applicable Clause(s) / subclause(s) of EN 50549-10:2022	Remark	Verdict
4.4.2 Operating frequency range	5.2.1 Frequency operating range	---	PASS
4.4.3 Minimal requirement for active power delivery at underfrequency	5.2.1 Frequency operating range	---	PASS
4.4.4 Continuous operating voltage range	5.2.2 Voltage operating range	---	PASS
4.5.2 Rate of change of frequency (ROCOF) immunity	5.3.1 Immunity to disturbances - Rate of change of frequency (ROCOF)	---	PASS
4.5.3.2 Generating plant with non-synchronous generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	Generating units of non-synchronous generating technology.	PASS
4.5.3.3 Generating plant with synchronous generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	---	N/A
4.5.4 Over-voltage ride through (OVRT)	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	---	PASS
4.5.5 Phase jump immunity	5.3.2 Phase jump	---	PASS
4.6.1 Power response to overfrequency	5.4 Active response to frequency deviation	---	PASS
4.6.2 Power response to underfrequency	5.4 Active response to frequency deviation	---	PASS
4.7.2.2 Voltage support by reactive power, Capabilities	5.5.1 Power capabilities assessment	---	PASS
4.7.2.3 Voltage support by reactive power, Control modes	5.5.2 Voltage support by reactive power - test to determine the reactive power control modes	Available modes: • Q setpoint • Q(U) • Q(P) • cosφ setpoint • cosφ(P)	PASS
4.7.2.3.2 Set point control modes	5.5.2.3 Verification procedure for Set point control	---	PASS
4.7.2.3.3 Voltage related control modes	5.5.2.5 Verification procedure for power related control modes for reactive power	---	PASS
4.7.2.3.4 Power related control mode	5.5.2.5 Verification procedure for power related control modes for reactive power	---	PASS
4.7.3 Voltage related active power reduction	5.6 Voltage related active power reduction - P(U)	---	PASS
only EN 50549-2:2019 4.7.4.2.1.1 Voltage support during faults and voltage steps – General	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	EN 50549-2 is not within the scope of this certification.	N/A

Annexe au certificat n°. / Annex to the Certificate No.: **LS250054GCC-0**

Clause(s) / subclause(s) of EN 50549-1:2019 or EN 50549-2:2019	Applicable Clause(s) / subclause(s) of EN 50549-10:2022	Remark	Verdict
only EN 50549-2:2019 4.7.4.2.1.2 Voltage support during faults and voltage steps - Optional Modes	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	EN 50549-2 is not within the scope of this certification.	N/A
4.7.4.2.2 Zero current mode for converter connected generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	---	PASS
4.8 EMC and power quality	5.7 EMC and power quality	---	PASS
only EN 50549-1:2019 4.9.3 Requirements on voltage and frequency protection	5.8.3 Verification procedure for generating plants to be connected to a LV distribution network with Interface protection as internal device or 5.8.4 Verification procedure for generating plants to be connected to a LV distribution network with Interface protection as dedicated device	The AC output is redundantly switched off by: - a high-power switching bridge - two relays for both the line conductor and the neutral conductor (Relay Model: Hongfa HF161F-W/12-HT(477) Alternative: Churod CHFV-V-112HA2F(35A) This ensures that the output circuit will be opened even in the event of a single failure. Available protection functions: - Voltage protection - Overvoltage 10 min mean protection - Frequency protection The settings of the function, as well as the enabling and disabling of the function, are field adjustable and are protected from unauthorized interference through password.	PASS
only EN 50549-2:2019, 4.9.3. Requirements on voltage and frequency protection	5.8.5 Verification procedure for generating plants to be connected to a MV distribution network	EN 50549-2 is not within the scope of this certification.	N/A
4.9.4 Means to detect island situation	5.8.6 Islanding detection	Islanding Detection Technique: Active Frequency Drift	PASS
4.10.2 Automatic reconnection after tripping	5.9.3 Automatic reconnection after tripping	---	PASS
4.10.3 Starting to generate electrical power	5.9.4 Starting to generate electrical power	---	PASS
4.11.1 Ceasing active power	5.10 Active power reduction on set point	The units provide logic interface for terminating active power output.	PASS
4.11.2 Reduction of active power on set point	5.10 Active power reduction on set point	---	PASS
4.12 Remote information exchange	5.11 Remote information exchange	Need to be evaluated at the project level.	N/A
only EN 50549-1:2019, 4.13 single fault tolerance of interface protection system and interface switch	5.12 Requirements regarding single fault tolerance of interface protection system and interface switch	---	PASS
	5.13 Model definition and model validation for generating units of synchronous generating technology	Generating units of non-synchronous generating technology.	N/A

A.5 Liste des paramètres / Parameter list

Name of parameter set		"018-001"				
Clause(s) / subclause(s) of EN 50549-1:2019+A1:2023	Parameter	Remarks / additional information	configurable value range	Step size	unit	default value
4.3.2 Interface switch	Single fault tolerance for interface switch	---	yes no	---	---	yes
4.4.2 Operating frequency range	47.0 – 47.5 Hz Duration	---	0 – 20 s	---	---	0s
	47.5 – 48.5 Hz Duration	---	30 – 90 min	---	---	≥30 min
	48.5 – 49.0 Hz Duration	---	30 – 90 min	---	---	≥30 min
	49.0 – 51.0 Hz Duration	---	not configurable	---	---	unlimited
	51.0 – 51.5 Hz Duration	---	30 – 90 min	---	---	≥30 min
	51.5 – 52 Hz Duration	---	0 – 15 min	---	---	0 min
4.4.3 Minimal requirement for active power delivery at under frequency	Reduction threshold	---	49 Hz – 49.5 Hz	---	---	Electronic inverter no power reduction take place
	Maximum reduction rate	---	2 – 10 % P _M /Hz	---	---	≤ 2 %
4.4.4 Continuous operating voltage range	Upper limit	---	230.0 – 276.0	0.1	V	253.0
	Lower limit	---	115.0 – 230.0	0.1	V	195.5
4.5.2 Rate of change of frequency (ROCOF) immunity	ROCOF withstand capability (defined with a sliding measurement window of 500 ms) non-synchronous generating technology: synchronous generating technology:	---	not defined	---	---	≥2 Hz/s
4.5.3.2 Generating plant with non- synchronous generating technology (FRT) Under-voltage ride through (UVRT)	Maximum power resumption time	Gradient for active power increase after fault recovery	0 - 30000	---	%P _n /min	30000
	Enable under voltage ride through	---	Enable disable	---	---	enable
	Voltage-Time-Diagram	LVRT Protection Level	see Figure 6. EN 50549-1	---	---	Time [ms] U [%Un]
	LVRT Voltage 1		0-100	1	%Un	400 4
	LVRT Time 1		0-65535	1	ms	
	LVRT Voltage 2		0-100	1	%Un	1000 25
	LVRT Time 2		0-65535	1	ms	
	LVRT Voltage 3		0-100	1	%Un	1850 50
	LVRT Time 3		0-65535	1	ms	
	LVRT Voltage 4		0-100	1	%Un	3000 50
	LVRT Time 4		0-65535	1	ms	
4.5.4 Over-voltage ride through (OVRT)	Enable over voltage ride through	---	Enable disable	---	---	enable
	Voltage-Time-Diagram	OVRT Protection Level	see Figure 8. EN 50549-1	---	---	Time [ms] U [%Un]

Name of parameter set		"018-001"					
Clause(s) / subclause(s) of EN 50549-1:2019+A1:2023	Parameter	Remarks / additional information	configurable value range	Step size	unit	default value	
	OVRT Voltage 1		0-130	1	%Un	120	125
	OVRT Time 1		0-65535	1	ms		
	OVRT Voltage 2		0-130	1	%Un	5050	120
	OVRT Time 2		0-65535	1	ms		
	OVRT Voltage 3		0-130	1	%Un	60050	120
	OVRT Time 3		0-65535	1	ms		
	OVRT Voltage 4		0-130	1	%Un	60100	120
	OVRT Time 4		0-65535	1	ms		
4.6.1 Power response to over frequency (LFSM-O)	Threshold frequency f1	---	50.20 – 52.00	0.01	Hz	50.20	
	Droop	---	17 – 100	1	%Pn/ Hz	40	
	Power reference	---	P_M P_{max}	0.1	% P_M	P_M	
	Intentional delay	---	0 – 2000	1	ms	0	
	Deactivation threshold fstop	---	50.00 Hz – f_1	0.01	Hz	deactivated	
	Deactivation time tstop	---	0-600000	1	ms	N/A	
	Acceptance of staged disconnection	---	yes no	---	---	no	
4.6.2 Power response to under frequency	Threshold frequency f1	---	49.80 – 46.00	0.01	Hz	49.80	
	Droop	---	17 – 100	1	%Pn/ Hz	40	
	Power reference	---	P_M P_{max}	0.1	% P_M	P_M	
	Intentional delay	---	0 – 2000	1	ms	0	
4.7.2.2 Capabilities	Active factor range overexcited	---	90.00 – 100.00	0.01	%	100.00	
	Active factor range underexcited	---	90.00 – 100.00	0.01	%	100.00	
4.7.2.3 Control modes	Enabled control mode	---	Q setp. Q(U) Q(P) cos ϕ setp. cos ϕ (P)	---	---	All can be set!	
4.7.2.3.2 Set point control modes	Q setpoint and excitation	---	0 – 48.43	0.01	%Pn	disabled	
	cos ϕ setpoint and excitation	---	90.00 – 100.00	0.01	%	disabled	
4.7.2.3.3 Voltage related control modes	Characteristic curve	---	Q(U) P(U)	---	---	disabled disabled	
	Time constant	---	3 – 60	1	s	disabled	
	Min cos ϕ	---	0.00 – 100.00	0.01	%	disabled	
	Lock in power	---	0 – 20	1	%Pn	deactivated	
	Lock out power	---	0 – 20	1	%Pn	deactivated	
4.7.2.3.4 Power related control mode	Characteristic curve	---	cos ϕ (P)	---	---	disabled	
4.7.4.2.2 Zero current mode for converter connected generating technology	Enabling	---	enable disable	---	---	enable	
	Static voltage range overvoltage	---	100 – 120	1	%Un	120	
	Static voltage range undervoltage	---	20 – 100	1	%Un	50	

Name of parameter set		"018-001"				
Clause(s) / subclause(s) of EN 50549-1:2019+A1:2023	Parameter	Remarks / additional information	configurable value range	Step size	unit	default value
4.9.2 Requirements on voltage and frequency protection	Threshold for protection as dedicated device [in A or kW. kVA]	---	0 – 250 kVA	---	---	N/A
	Undervoltage threshold stage 1	---	46.0 – 230.0	0.1	V	195.5
	Undervoltage operate time stage 1	---	10 – 100000	10	ms	1200
	Undervoltage threshold stage 2	---	46.0 – 230.0	0.1	V	175.0
	Undervoltage operate time stage 2	---	10 – 5000	10	ms	100
	Overvoltage threshold stage 1	---	230.0 – 276.0	0.1	V	264.5
	Overvoltage operate time stage 1	---	10 – 100000	10	ms	140
	Overvoltage threshold stage 2	---	230.0 – 299.0	0.1	V	273.0
	Overvoltage operate time stage 2	---	10 – 5000	10	ms	100
	Overvoltage threshold 10 min mean protectiona	---	230.0 – 264.5	0.1	V	253.0
	Overvoltage operate time 10 min mean protectiona	Internal parameter not configurable	0 – 3 s	---	---	10 min (update every 3s)
	Underfrequency threshold stage 1	---	47.00 – 50.00	0.01	Hz	47.50
	Underfrequency operate time stage 1	---	10 – 100000	10	ms	300
	Underfrequency threshold stage 2	---	47.00 – 50.00	0.01	Hz	disabled
	Underfrequency operate time stage 2	---	10 – 5000	10	ms	disabled
	Overfrequency threshold stage 1	---	50.00 – 52.00	0.01	Hz	52.00
	Overfrequency operate time stage 1	---	10 – 100000	10	ms	300
	Overfrequency threshold stage 2	---	50.00 – 52.00	0.01	Hz	disabled
	Overfrequency operate time stage 2	---	10 – 5000	10	ms	disabled
	Loss of mains according EN 62116 (LoM)	Internal parameter not configurable	0 - 6000s	---	---	2.5 Hz/s (0.5s)
4.10.2 Automatic reconnection after tripping	Lower frequency	---	47.00 – 50.00	0.01	Hz	49.50
	Upper frequency	---	50.00 – 52.00	0.01	Hz	50.20
	Lower voltage	---	115.0 – 230.0	0.1	V	195.5
	Upper voltage	---	230.0 – 276.0	0.1	V	253.0
	Observation time	---	10 – 600	1	s	60
	Active power increase gradient	---	6 – 3000	1	%Pn/min	10
4.10.3 Starting to generate electrical power	Lower frequency	---	47.00 – 50.00	0.01	Hz	49.50
	Upper frequency	---	50.00 – 52.00	0.01	Hz	50.10

Name of parameter set		"018-001"				
Clause(s) / subclause(s) of EN 50549-1:2019+A1:2023	Parameter	Remarks / additional information	configurable value range	Step size	unit	default value
	Lower voltage	---	115.0 – 230.0	0.1	V	195.5
	Upper voltage	---	230.0 – 276.0	0.1	V	253.0
	Observation time	---	10 – 600	1	s	60
	Active power increase gradient	---	6 – 3000	1	%Pn/min	100
4.11.1 Ceasing active power	Remote operation of the logic interface	---	yes no	---	---	Yes (RS485. DI)
4.11.2 Reduction of active power on set point	Remote operation NOTE: If yes further definition is provided by the DSO	---	yes no	0.1	%Pn	Yes (RS485. DI)